



University of Bahrain

CE -- CIT -- UOB

TEST 1 (6 April 2016) ITCE 444:  $\mu$ P-Based Design

Dr. Riyadh Al-Hakim

Time: 60 minutes

**Q1.** [25 marks]

After running the following instructions what will be the contents of WREG, R1 and status flags?

```
R1    EQU    0x10
      MOVLW  0x7F
      MOVWF  R1
      INCF   R1, F
      INCF   R1, W
      INCF   R1, W
      INCF   R1, W
H:    BRA    H
```

**Q2.** [25 marks]

Assemble the following program:

```
ORG 0x005678
BACK: MOVFF  PORTE,PORTA
      LFSR   2,345 0x345
      BNZ    BACK
      GOTO   BACK
HERE: BRA    HERE
```

**Q3.** [ 50 marks]

A 6-bit unsigned number ( **X** ) is presented by 6 switches connected to port B.

A 7-bit unsigned number ( **Y** ) is presented by 7 switches connected to port C.

Write a program to read these two numbers and calculate  $Z = 2(X^2 + Y^2)$  and save **Z** in 0x300.